


- 1) The IS31 is designed to install at the radio antenna connection usually located on the back of the radio in the dash. In some cases this connection may be at a remote radio tuner location. Consult vehicle manufacturer's information in these cases.
- 2) Some antenna connections require the use of an antenna adapter in order to connect to the IS31. These adapters are available from most car audio installation retailers.
- 3) The IS31 broadcasts audio via two specific FM frequencies. Please choose the one that is unoccupied by a local radio station and set the switch to the respective frequency. For your convenience, set PRESET #1 on your radio to the selected broadcast frequency for quick and easy recall later.
- 4) Once the IS31 is installed according to the diagram to the right, be sure to properly set the audio level. When set correctly, the audio level of the IS31 will match the volume of typical FM radio stations.
- 5) To use the IS31, first set the switch to ON position. Next, press your stored preset to tune to the broadcasting frequency. Operate your audio device as usual and enjoy your music!

Radio Tuning Frequency

Use to select best operating frequency for your area

Audio Input
Left & Right



Gain Adjustment

Use to match volume of IS31 to volume of FM radio stations

Antenna Out
to FM radio*


Antenna Input
from vehicle antenna*

Ground Connection
Connect to a clean ground point

On/Off Switch
3/4" mounting hole

Connects to Power Source
ACC 12VDC
Power when key-on

2A Fuse



* Some radios require the addition of antenna connection adapters

For best performance have it professionally installed



iSimple®
A Division of AAMP of America™
13190 56th Court, Clearwater, FL 33760
866-788-4237
support@isimplesolutions.com
©2009 AAMP of Florida Inc.